





Application







Emergency

Camping

Camper



500Wh LFP battery



500W Inverter



1×Type C 60W ← : 2× QC 3.0 18W 2× QC 2.0 10W



• 12V 10A



5W-7.5W-10W

IDEAL FOR PHONES, TABLETS, LAPTOPS, CAMERA BATTERIES **AND MORE**

Comprehensive LCD Display

Battery level, output watts / voltage, AC output / input voltage/frequency, working mode, etc. are all easy to learnt by its comprehensive LCD display. Working parameters are on-line monitoring.

Universal Compatibility

Equipped with multiple output ports to power mainstream essential gadgets and small appliances at the push of a button.

Multiple Charging

Solar(100W, optional) charging, AC charging and in-car cigarette lighter charging are all available for charging DDS500-A. Always keep the power with the adventure.

Battery capacity	Lithium battery 500Wh
Continuous AC power	500W
Overload protection	$520\pm10 ext{W}$
Peak output power	1000W
Output waveform	Pure sine wave
AC input voltage	100-240VAC 50/60Hz
AC output voltage	100V / 110V or 220V / 240V; 50Hz / 60Hz
AC output protection	Over/low voltage, short circuit, overload, over temperature protection
Type-C	60A Max., 5V-20V
QC 3.0	2×18W Max., 5V-12V
QC 2.0	2×5V / 4A
Cigarette lighter port	12V / 10A
Solar input watt	Max. 100W
Wireless Charging	5W-7.5W-10W
Dimension	340×195×210 mm (13.4×7.7×8.3 in)
Weight	7 Kg (15.4 lb)